



The drafting committee of Jump Starter Industry Standard in China  
A supplier of global professional Multi-function emergency jump starter solutions

# Powerful Multi-function Jump Starter Wireless Charging



## Product Specification

Model :	<b>6600</b>	<b>10000</b>
BatterCapacity :	6600mAh(24.2Wh)	10000mAh(37Wh)
Size :	151*81*25mm	151*81*32mm
Weight :	325g	395g
Input :	Quick Charge(5V/2A;9V/2A)	
Output :	Quick Charge(5V/2.4A;9V/2A); 5V/2.1A Wireless charging 10W Max 12V Jump start	
Full charging time :	About 1.5 hours	About 2 hours
Start Current :	150A	200A
Peak Current :	400A	500A
Operating Temp :	-20°C~60°C	
Lifetime :	> 1000cycles	



Jump start



3C digital  
products charge



SOS/Lighting



Wireless charging

## Wireless Charging Specification

Working Voltage :	5V
Working Current :	1A-2A
Transmitting Power :	5W/7.5W/10W
Working Frequency :	105KHz-205KHz
Working Distance :	8mm

## PRODUCT LAYOUT :



## Product Highlight :

- 1 · Jump under 3.5L gasoline cars
- 2 · Quick Charge output charge for digital product
- 3 · Wireless charging for your mobile
- 4 · 3Pins intelligent clamps, more protection.
- 5 · ABS housing in V0 Anti-fire grade
- 6 · UL approved Lithium Polymer battery assure functions
- 7 · Long cycle life over 1000 cycles

## Accessories :











Mobile connectors



Smart Jumper Cable

## Safety Design Eight Protections

- |  |   |
|--|---|
| <p> <b>Short-Circuit Protection</b><br/>Prevent short-circuit occurring while two clamps are connected</p>         | <p> <b>Over-temperature Protection</b><br/>Automatically stop working when the temperature is getting too high</p>         |
| <p> <b>Over-charge protection</b><br/>Effectively prevent over-charge of the battery in the jump starter</p>       | <p> <b>Reverse Polarity Protection</b><br/>No damage occurs if the clamps are connected to the wrong battery terminals</p> |
| <p> <b>Over-discharge protection</b><br/>Effectively prevent over-discharge of the battery in the jump starter</p> | <p> <b>Reverse-charge Protection</b><br/>No reverse charging back to Carku unit after the vehicle started</p>              |
| <p> <b>Over-current protection</b><br/>Protection when the discharge current is too high</p>                       | <p> <b>Over-voltage protection</b><br/>Prevents huge differences in cell-to-cell voltage</p>                               |

